

## Настройка Cisco SPA303

1. Подключить Cisco к сети электропитания и к интернету.
2. Узнать IP адрес можно через панель телефона, нажав на клавишу MENU (листочек с отогнутым краем) → Network (клавиша 9) → Current IP (клавиша 2).
3. В верхней строке отобразится IP-адрес телефона. Вводим этот адрес в адресной строке вашего браузера (например 192.168.0.100). Откроется Web-интерфейс телефона.
4. Вход на web-интерфейс осуществляется без пароля.
5. При нажатии Admin login и далее Advanced - в правом верхнем углу окна, откроются расширенные настройки устройства.



6. Открываем вкладку Ext 1 заполняем следующие поля:

Small Business  
**CISCO SPA303 Configuration Utility** User Login basic | advanced

Voice Call History Personal Directory

Info System SIP Provisioning Regional Phone User Attendant Keys

Ext 1 Ext 2 Ext 3

**General**  
 Line Enable:  yes

**Share Line Appearance**  
 Share Ext: private  
 Subscription Expires: 3000  
 Monitor User ID:  
 Shared User ID:  
 Restrict MW: no

**NAT Settings**  
 NAT Mapping Enable:  yes  
 NAT Keep Alive Map: NOTIFY  
 NAT Keep Alive Enable:  yes  
 NAT Keep Alive Dest: NOTIFY

**Network Settings**  
 SP TOGDISServ Value: 0x00  
 RTP TOGDISServ Value: 0x00  
 Network Jitter Level: high  
 SP CoS Value: 2  
 RTP CoS Value: 6  
 Jitter Buffer Adjustment: up and down

**SIP Settings**  
 SIP Transport: UDP  
 SIP 100REL Enable: no  
 Auth Reauth-Reboot: yes  
 SIP Remote-Party-ID: no  
 Refer-To Target Contact: no  
 SIP Debug Option: none  
 Sticky 100: no  
 Nty Refer On Fax-To-Inv: yes  
 Set G729 annex: none  
 SIP Port: 5061  
 EXT SIP Port:  
 SIP Proxy-Require:  
 Referor Bye Delay: 4  
 Referor Bye Delay: 0  
 Refer Target Bye Delay: 0  
 Auth INVITE: no  
 Use Anonymous With RPD: yes  
 Voice Quality Report Address:

**Call Feature Settings**  
 Blind Aft-Xfer Enable: no  
 Message Waiting: no  
 Default Ring: 1  
 Conference Bridge URL:  
 Mailbox P:  
 MCH Server:  
 Auth Page: no  
 Auth Page Realm:  
 Auth Page Password:  
 Voice Mail Server:

Undo All Changes Submit All Changes

© 2009 Cisco Systems, Inc. All Rights Reserved. SPA303 IP Phone

**Proxy and Registration**  
 Proxy: voip.uiscm.ru:5060  
 Register:  yes  
 Register Expires: 300  
 Make Call Without Reg: no  
 Ans Call Without Reg: no

**Subscriber Information**  
 Display Name: Sip Login  
 Password: Sip password  
 Auth ID: Sip Login  
 User ID: Sip Login  
 Use Auth ID:  yes

**Audio Configuration**  
 Preferred Codec: G711a  
 Second Preferred Codec: unspecified  
 Silence Supp Enable: no  
 Use Pref Codec Only: no  
 Third Preferred Codec: Unspecified  
 DTMP Tx Method: Auto

Undo All Changes Submit All Changes

© 2009 Cisco Systems, Inc. All Rights Reserved. SPA303 IP Phone

7. Нажимаем «Submit All Changes».

8. Настройка завершена.